SubSpace 50/70

Trim Recessed mounted Linear System

SubSpace 50/70

As Standard

- Max Luminaire housing length 3m (nominal).
- Housing Supplied as either: Individual (IND), End of Run (EOR) or Intermediate (INT).
- Fixing Brackets pre installed as standard.
- Jointing kits are packaged separately, please check thoroughly before installing and report any missing components.

Recessed with trim

Nominal Lengths						
Products	**SubSpace 50**			**SubSpace 70**		
	W	*H*	*Kg*	*W*	*H*	*Kg*
870mm	60	80	2.0	85	80	2.7
1150mm	60	80	2.6	85	80	3.5
1430mm	60	80	3.3	85	80	4.4
1710mm	60	80	3.9	85	80	5.2
1990mm	60	80	4.5	85	80	6.0
2270mm	60	80	5.2	85	80	7.0
2550mm	60	80	5.8	85	80	7.8
2970mm	60	80	6.7	85	80	9.0

SubSpace 50/70

3 Please cut-out rectangular hole in desired surface (Please use length as per quote and use inconjuction with table below).

Nominal Lengths				
SubSpace 50			**SubSpace 70**	
Trim			***Trim***	
L (A)	*W (B)*		*L (A)*	*W (B)*
L* + 5mm	55		**L* + 5mm**	78

* Please replace L with quoted length

Example diagram

2 Remove front diffuser using pre installed release tabs, store diffuser safely until required later.

3 **A.** Press gear tray releasing springs and gently pull gear tray out. **B.** Unclip pre installed safety cord clips at either and of the gear tray.

1 For Recessed trim, Insert trim housing into prepared aperture.

2 **A.** Using a the pozidrive screwhead inside the luminaire housing, gently turn until twist-out brackets are fully open. **B.** To tighten down brackets continue turning until frame is secure against the ceiling.

3

For continuous systems, Install Joint fastening bracket to each respective body, Ensure 2mm joint channel centre holes line up with edge of housing, secure in place. Repeat for all joints. For individual luminiare installation please skip to step 5, for continuous systems please continue.

4

Slide the two housings together, ensure joint channel slides in evenly into the groove on the adjoining body, once connected use M4x20 screw to pull joint together.

5 Feed Incoming flex (provided by others) through the cable gland. Connect feed into to the terminal block (See pages 9-11 for all wiring diagrams).

6 For through wiring, please connect supplied feed to all respective terminal blocks on each gear tray. (See pages 8 - 12 for through wiring diagrams).

Through wiring example image

7 Once all connected, lift up a gear tray and secure to housing using pre installed safety cord clips at either end of the gear tray.

8 Once the luminaire has been wired . Gently push all the gear trays into the springs so that it sits a per diagram below.
Check all are secure.

!!PLEASE DO NOT!!
Over push gear tray into springs, please ensure gear tray is postioned as per diagram shown

9 Re install all the diffusers back into the main housing ensuring they all click back into the body evenly.

10

A

Fixed Output.

- Live
- Earth
- Neutral

B

Fixed Output Emergency Wiring.

- Live
- Earth
- Neutral
- Unswitched Live

C DALI Wiring.

- Live
- Earth
- Neutral
- DALI
- DALI

D DALI Emergency Wiring.

- Live
- Earth
- Neutral
- Unswitched Live
- DALI
- DALI

E

SwitchDIM Wiring.

- Live
- Earth
- Neutral
- Variable Live

Example switchDIM circuit
220-240 V
0/50/60 Hz

F Fixed Output Through Wiring.

- Live
- Earth
- Neutral

G Fixed Output Emergency through Wiring.

- Live
- Earth
- Neutral
- Unswitched Live

H DALI/DSI Through Wiring.

- Live
- Earth
- Neutral
- DALI
- DALI

I DALI/DSI Emergency Through Wiring.

- Live
- Earth
- Neutral
- Unswitched Live
- DALI
- DALI

SubSpace 50/70

Safety

- This luminaire should be installed by a qualified electrician in compliance with IEE regulations.
- Please ensure mains supply to luminaire is disconnected before installation or maintenance.
- The light source contained in this luminaire shall only be replaced by the manufacturer or his service agent or a similar qualified person.

Ratings

- This luminaire is designed to operate at 230VAC -6% +10% 216v to 252v. DO NOT OPERATE OUTSIDE THIS RANGE.
- This luminaire is only suitable for installation within its rated ingress Protection limits.

Subject to change without notice. Errors and omission excepted.
Always make sure to use the most recent release.

LED

IP20

MADE IN BRITAIN®

CROWN HOUSE, PLANTATION RD,
BURSCOUGH, LANCASHIRE. L40 8JT
01704 891 333
www.pandaprojects.co.uk